

# **SHOWPRO**

**LEDCUR001**

EA-9083B

Tri-Colour RGB Star Curtain User Manual

Manual Mode:

1	rL 15	Red Dimmer
2	gL 15	Green Dimmer
3	bL 15	Blue Dimmer

Auto Mode:

1	FL 15	Flash
2	FA 15	Automatic fade in and fade out
3	AS 15	Auto change 7 colours
4	cE 15	Chase Strings
5	cS 15	Chase Speed

Sound Control Mode:

1	SQVA	Sound Chase
2	SQVF	Sound Auto Colour Change
3	SENS	Sound Sensitivity 00 to 15

Synchronized Mode (Master/Slave):

Master	Choose Auto/Manual/Sound mode needed.
Slave	ADD 1

**DMX Channel Profiles:**

Mode **R** (3CH)

DMX Channel	Function	Description	Value
1	Dimmer	Master Intensity	0-255
2	Macro Effect	Macro 1	0-15
		Macro 2	16-30
		Macro 3	31-45
		Macro 4	46-60
		Macro 5	61-75
		Macro 6	76-90
		Macro 7	91-105
		Macro 8	106-120
		Macro 9	121-135
		Macro 10	136-150
		Macro 11	151-165
		Macro 12	166-180
		Macro 13	181-195
		Macro 14	196-210
		Macro 15	211-225
		Macro 16	226-240
		Macro 17	241-255
3	Macro Speed	Speed of Macro Selected	0-255

Mode **P** (24CH)

DMX Channel	Function	Description	Value
1	Strand 1 Red	Strand 1 Red Intensity	0-255
2	Strand 1 Green	Strand 1 Green Intensity	0-255
3	Strand 1 Blue	Strand 1 Blue Intensity	0-255
4	Strand 2 Red	Strand 2 Red Intensity	0-255
5	Strand 2 Green	Strand 2 Green Intensity	0-255
6	Strand 2 Blue	Strand 2 Blue Intensity	0-255
7	Strand 3 Red	Strand 3 Red Intensity	0-255
8	Strand 3 Green	Strand 3 Green Intensity	0-255
9	Strand 3 Blue	Strand 3 Blue Intensity	0-255
10	Strand 4 Red	Strand 4 Red Intensity	0-255
11	Strand 4 Green	Strand 4 Green Intensity	0-255
12	Strand 4 Blue	Strand 4 Blue Intensity	0-255
13	Strand 5 Red	Strand 5 Red Intensity	0-255
14	Strand 5 Green	Strand 5 Green Intensity	0-255
15	Strand 5 Blue	Strand 5 Blue Intensity	0-255
16	Strand 6 Red	Strand 6 Red Intensity	0-255
17	Strand 6 Green	Strand 6 Green Intensity	0-255
18	Strand 6 Blue	Strand 6 Blue Intensity	0-255
19	Strand 7 Red	Strand 7 Red Intensity	0-255
20	Strand 7 Green	Strand 7 Green Intensity	0-255
21	Strand 7 Blue	Strand 7 Blue Intensity	0-255
22	Strand 8 Red	Strand 8 Red Intensity	0-255
23	Strand 8 Green	Strand 8 Green Intensity	0-255
24	Strand 8 Blue	Strand 8 Blue Intensity	0-255

Mode **F** (32CH)

DMX Channel	Function	Description	Value
1	Strand 1 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
2	Strand 1 Red	Strand 1 Red Intensity	0-255
3	Strand 1 Green	Strand 1 Green Intensity	0-255
4	Strand 1 Blue	Strand 1 Blue Intensity	0-255
5	Strand 2 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
6	Strand 2 Red	Strand 2 Red Intensity	0-255
7	Strand 2 Green	Strand 2 Green Intensity	0-255
8	Strand 2 Blue	Strand 2 Blue Intensity	0-255
9	Strand 3 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
10	Strand 3 Red	Strand 3 Red Intensity	0-255
11	Strand 3 Green	Strand 3 Green Intensity	0-255
12	Strand 3 Blue	Strand 3 Blue Intensity	0-255
13	Strand 4 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
14	Strand 4 Red	Strand 4 Red Intensity	0-255
15	Strand 4 Green	Strand 4 Green Intensity	0-255
16	Strand 4 Blue	Strand 4 Blue Intensity	0-255
17	Strand 5 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
18	Strand 5 Red	Strand 5 Red Intensity	0-255
19	Strand 5 Green	Strand 5 Green Intensity	0-255
20	Strand 5 Blue	Strand 5 Blue Intensity	0-255
21	Strand 6 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
22	Strand 6 Red	Strand 6 Red Intensity	0-255
23	Strand 6 Green	Strand 6 Green Intensity	0-255
24	Strand 6 Blue	Strand 6 Blue Intensity	0-255
25	Strand 7 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
26	Strand 7 Red	Strand 7 Red Intensity	0-255
27	Strand 7 Green	Strand 7 Green Intensity	0-255
28	Strand 7 Blue	Strand 7 Blue Intensity	0-255
29	Strand 8 Dimmer/Strobe	Dimmer	0-152
		Strobe	153-242
		Dimmer 100%	243-255
30	Strand 8 Red	Strand 8 Red Intensity	0-255
31	Strand 8 Green	Strand 8 Green Intensity	0-255
32	Strand 8 Blue	Strand 8 Blue Intensity	0-255

